



# PIN OUT:

| P1    |              | P2    |
|-------|--------------|-------|
| 1     | red(20awg)   | 1     |
| 2     | white(28awg) | 2     |
| 3     | green(28awg) | 3     |
| 4     | black(20awg) | 4     |
| shell | braid+drain  | shell |

| ITEM | PART NO.             | DESCRIPTION                                                 | REMARK |
|------|----------------------|-------------------------------------------------------------|--------|
| 1    | 5075A-02-02-30-F1    | USB A SOLDER TYPE MALE TERMINAL GOLD 30U"                   | 1      |
| 2    | 5075B-02-02-30-F1    | USB B SOLDER TYPE MALE TERMINAL GOLD 30U"                   | 1      |
| 3    | 810B-1P2C2820B5.0BG3 | UL 2725 28AWG*1P+20AWG*2C+AEB OD:5.0MM COLOR:BEIGE (2.0REV) | 1      |
| 4    | 829A-R14.2*28.5*6.7  | FERRITE CORE OD*H*ID=14.2*28.5*6.7MM                        | 1      |
| 5    | 827-PVC-45P-BG       | PVC MOLDING COLOR:BEIGE                                     |        |

# NOTES:

1. ALL DIMENSIONS ARE IN MM UNLESS NOTED OTHERWISE.

CABLE LENGTH:  
2 METERS

|                                       |          |              |                     |          |                                                                |
|---------------------------------------|----------|--------------|---------------------|----------|----------------------------------------------------------------|
| MATERIAL:                             | ASSEMBLY | DRAWN BY:    | M. ABRAMOVICH       | 10/20/06 | <b>HO CHIEN</b><br>www.hochien.com<br><b>PN# CA-B2045-0002</b> |
| TOLERANCES UNLESS OTHERWISE SPECIFIED |          | APPROVED BY: |                     | 2250-151 |                                                                |
|                                       |          | ENG:         | <i>Paul Kuo</i>     | 10/22/06 |                                                                |
|                                       |          | MFG:         | <i>Paul Kuo</i>     | 10/23/06 |                                                                |
|                                       |          | QA:          | <i>JR. Morrison</i> | 10/23/06 | <b>USB A/B 2M BEIGE CABLE W/FERRITE</b>                        |